

# Product Manual

## Intelligent Helmet Bluetooth Headset




• PACKAGE CONTENTS




MAXRUNON 2X  
Main Unit




Back Clip



3M Glue Plate



Speaker Unit  
Hybrid Microphone



Velcro for Speaker



Velcro for Hybrid Mic



Type-C Cable



Manual

## RF EXPOSURE STATEMENT

This equipment complies with the FCC and ICSED radiation exposure limits set forth for an uncontrolled environment. This transmitter must not be co-located or operating in conjunction with any other antenna or transmitter.

Cet équipement est conforme aux limites d'exposition aux rayonnements de la FCC et de l'ICSED établies pour un environnement non contrôlé. Cet émetteur ne doit pas être co-localisé ou fonctionner en conjonction avec une autre antenne ou un autre émetteur.

## FCC WARNING

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

(1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Note: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

—Reorient or relocate the receiving antenna.

—Increase the separation between the equipment and receiver.

—Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.

—Consult the dealer or an experienced radio/TV technician for help.

NOTE 2: Any changes or modifications to this unit not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

## IC WARNING

This device contains licence-exempt transmitter(s) that comply with Innovation, Science and Economic Development Canada's licence-exempt RSS(s). Operation is subject to the following two conditions:

(1) This device may not cause interference.


(2) This device must accept any interference, including interference that may cause undesired operation of the device.

L'émetteur/récepteur exempt de licence contenu dans le présent appareil est conforme aux CNR d'Innovation, Sciences et Développement économique Canada applicables aux appareils radio exempts de licence. L'exploitation est autorisée aux deux conditions suivantes:

1. L'appareil ne doit pas produire de brouillage;

2. l'appareil doit accepter tout brouillage radioélectrique subi, même si le brouillage est susceptible d'en compromettre le fonctionnement.

## • Function



-  Volume -
-  Volume +
-  Function button
-  Intercom button
-  Audio Interface
-  Type-C Charging Port

## • Product Specifications

|                             |                                                            |
|-----------------------------|------------------------------------------------------------|
| Product model               | 2X                                                         |
| Bluetooth name              | MAXRUNON 2X                                                |
| Bluetooth version           | 5.3                                                        |
| Microphone&speaker          | 40mm Speaker Unit Hybrid Microphone                        |
| Maximum intercom capacity   | 2 people                                                   |
| Communication distance      | 500m                                                       |
| Voice control               | Press the button to activate your phone's voice assistant. |
| Noise reduction capability  | 100 kilometers per hour, clear communication               |
| Waterproof rating           | IPX5                                                       |
| Battery capacity            | 500mAh                                                     |
| Software upgrade            | Non-support                                                |
| FM function                 | Support                                                    |
| Fast charging time          | 60 minutes                                                 |
| Standby time                | 170 hours                                                  |
| Intercom battery life       | 24 hours                                                   |
| Music playback battery life | 22 hours                                                   |
| Intercom+music battery life | 15 hours                                                   |
| Automatic audio adjustment  | support                                                    |

| Function                        | Button Operation                                                                                                                                                                            |
|---------------------------------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Power On/Off                    | +    2S                                                                                                                                                                                     |
| Play Music                      |                                                                                                                                                                                             |
| Pause Music                     |                                                                                                                                                                                             |
| Previous Track                  | + 3S                                                                                                                                                                                        |
| Next Track                      | - 3S                                                                                                                                                                                        |
| Volume +                        |                                                                                                                                                                                             |
| Volume -                        |                                                                                                                                                                                             |
| Answer Call                     | Any button                                                                                                                                                                                  |
| End Call                        |                                                                                                                                                                                             |
| Reject Call                     | 3S                                                                                                                                                                                          |
| Phone Pairing                   | 3S                                                                                                                                                                                          |
| Group Bluetooth Grouping        | <ul style="list-style-type: none"> <li>   2S</li> <li>○ After hearing the broadcast announcing the number of connected members.</li> <li>○   x1 Tap Confirm</li> </ul>                      |
| Group Mode                      |                                                                                                                                                                                             |
| Universal Mode                  | <ul style="list-style-type: none"> <li>   3S</li> <li>○ Other bluetooth headsets need to activate bluetooth pairing mode</li> <li>○  x2 Tap</li> <li>○  x2 Tap Activate intercom</li> </ul> |
| Cancel Group Bluetooth Grouping | 2S Cancel the group when you're in the group bluetooth grouping state.                                                                                                                      |

| Function                           | Button Operation                                                                                                                                                                                                                                                                                                                                                                                                                    |
|------------------------------------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Radio On                           |  ×2 Tap                                                                                                                                                                                                                                                                                                                                            |
| Radio Off                          |  ×2 Tap                                                                                                                                                                                                                                                                                                                                            |
| Search Radio Stations              | <br>Note: When FM is turned on                                                                                                                                                                                                                                                                                                                     |
| Factory Reset                      |  ++    3S<br>Note: The device will reboot and reset to the manufacturer settings.               |
| Microphone on/off                  |  +  +   2S<br>Note: Simultaneously long press the intercom button and any volume button for 2s. |
| Active the phone's voice assistant |  ×2 Tap                                                                                                                                                                                                                                                                                                                                            |